

DTC	P2111	THROTTLE ACTUATOR CONTROL SYSTEM - STUCK OPEN
------------	--------------	--

DTC	P2112	THROTTLE ACTUATOR CONTROL SYSTEM - STUCK CLOSED
------------	--------------	--

CIRCUIT DESCRIPTION

The throttle motor is operated by the ECM and it opens and closes the throttle valve by a gear. The opening angle of the throttle valve is detected by the throttle position sensor which is mounted on the throttle body. And, it provides feedback to the ECM to control the throttle motor in order to make the throttle valve opening angle properly in response to the driving condition. If this malfunction is detected, the ECM shuts down the power for the throttle motor, and the throttle valve is fully closed by the return spring. And the throttle valve is locked at a certain opening angle. Also, the whole electronically controlled throttle operation is cancelled until the system returns to normal and the ignition switch is turned OFF.

HINT:

This electrical throttle system is no used throttle cable.

DTC No.	DTC Detection Condition	Trouble Area
P2111	Lock the throttle motor during control the throttle motor (Stuck open)	<ul style="list-style-type: none"> • Throttle control motor circuit • Throttle control motor • Throttle body • Throttle valve
P2112	Lock the throttle motor during control the throttle motor (Stuck closed)	

WIRING DIAGRAM

Refer to DTC P2102 on page [05-182](#) .

INSPECTION PROCEDURE

HINT:

Read freeze frame data using the hand-held tester or the OBD II scan tool, as freeze frame data records the engine conditions when a malfunction is detected. When troubleshooting, it is useful for determining whether the vehicle was running or stopped, the engine was warmed up or not, the air-fuel ratio was lean or rich, etc. at the time of the malfunction.


1	INSPECT THROTTLE W/MOTOR BODY ASSY(VISUALLY CHECK THROTTLE VALVE)
----------	--

- (a) Check whether or not a foreign body is caught between the throttle valve and housing.

NG	REMOVE FOREIGN BODY AND CLEAN THROTTLE BODY
-----------	--

OK

2 INSPECT THROTTLE W/MOTOR BODY ASSY(RESISTANCE OF THROTTLE CONTROL MOTOR)



- Disconnect the throttle w/ motor body connector.
- Measure the motor resistance between terminal M+ and M-.

Motor resistance: 0.3 - 100 Ω at 20 °C (68 °F)

NG


REPLACE THROTTLE W/MOTOR BODY ASSY

OK

3 CHECK HARNESS AND CONNECTOR(THROTTLE CONTROL MOTOR - ECM)

Wire Harness Side

Throttle w/ Motor Body Connector



B53781


- Disconnect the throttle w/ motor body connector.
- Disconnect the E6 ECM connector.
- Check the continuity between the wire harness side connectors.

Standard (Check for open):

Symbols (Terminal No.)	Specified condition
M+ (2) \Leftrightarrow M+ (E6-3)	Continuity
M- (1) \Leftrightarrow M- (E6-2)	

Standard (Check for short):

Symbols (Terminal No.)	Specified condition
M+ (2) or M+ (E6-3) \Leftrightarrow Body ground	No continuity
M- (1) or M- (E6-2) \Leftrightarrow Body ground	



NG

REPAIR OR REPLACE HARNESS OR CONNECTOR

OK

CHECK FOR INTERMITTENT PROBLEMS (See page 05-5)